

Transformer Fault Current available at secondary Terminals based on Unlimited source					
Always Contact the Local Supplying Utility to verify Local Fault Current Ratings					
kVA	Type	Phase	Voltage	%Z	Short Circuit Amps (SCA)
37.5	Pole/pad	1	120/240	1.50	10,417
50	Pole/pad	1	120/240	1.50	13,889
75	Pole/pad/submersible	1	120/240	1.50	20,833
100	Pole/pad/submersible	1	120/240	1.60	26,042
167	Pole/pad	1	120/240	1.60	43,490
250	Pole	1	120/240	5.00	20,833
3 - 25	Pole	3	208Y/120	1.50	13,889
3 - 37.5	Pole	3	208Y/120	1.50	20,833
3 - 50	Pole	3	208Y/120	1.50	27,778
3 - 75	Pole	3	208Y/120	1.50	41,667
3 - 50	Pole	3	480Y/277	1.50	12,034
3 - 75	Pole	3	480Y/277	1.50	18,051
3 - 100	Pole	3	480Y/277	1.60	22,563
3 - 167	Pole	3	480Y/277	1.60	37,681
75	Pad	3	208Y/120	1.40	14,881
112.5	Pad	3	208Y/120	1.40	22,321
150	Pad	3	208Y/120	1.40	29,762
225	Pad	3	208Y/120	1.40	44,643
300	Pad	3	208Y/120	1.40	59,524
500	Pad	3	208Y/120	1.40	99,206
750	Pad	3	208Y/120	5.32	39,160
1000	Pad	3	208Y/120	5.23	52,214
150	Pad	3	480Y/277	1.40	12,893
225	Pad	3	480Y/277	1.40	19,340
300	Pad	3	480Y/277	1.40	25,786
500	Pad	3	480Y/277	1.40	42,977
750	Pad	3	480Y/277	5.23	16,965
1000	Pad	3	480Y/277	5.23	22,620
1500	Pad	3	480Y/277	5.23	33,930
2000	Pad	3	480Y/277	5.23	45,239
2500	Pad	3	480Y/277	5.23	56,549